

ACCU-GOLD T3

USER GUIDE



Simply Powerful

The Radcal Accu-Gold T3 is a state-of-the-art radiation quality control measurement system with software designed to provide accurate and reliable measurements for a wide range of applications. This instruction manual is designed to guide you through the features and functions of the software, so you can make the most of its capabilities.

With its advanced algorithms and sophisticated sensors, it is capable of making sophisticated measurements in real-time. With its user-friendly interface, Accu-Gold T3 is easy to use and understand, making it the perfect tool for anyone working with radiation.

The Radcal Accu-Gold T3 is the next generation x-ray measurement system that combines a portable standalone measurement system with software that has the ability to provide accurate and reliable dose measurements in real-time. This is achieved through the use of advanced algorithms and sophisticated sensors that are specifically designed to detect and measure radiation. The software also includes a range of customizable settings that allow users to tailor the measurement process to their specific needs.

At T3's core is the usage of profiles. Profiles are used to define the measurement process. They spell out trigger parameters, filtration requirements, the breakdown of the measurement (such as having a scout pulse) and the end of the pulse. Special calibrations are built into the profiles eliminating the need to install calibration files. Profiles allow you to specify different techniques for special measurements rather than relying on across-the-board catch-all techniques.

The T3 Pro with its Wi-Fi capability, adds to the ease of use of the AG3 software making it possible to have the T3 with its sensors hooked up connected wirelessly 10 meters or more to the computer running AG3.


System overview

Accu-Gold T3 has features to increase your productivity such as: quick setup, ease of use, automatic settings and multiple-parameter data capture, unique remote operation, easy data analysis, and instant data recall. With an Auxiliary sensor input and customizable software, you have the capability to expand to meet future needs.

The Accu-Gold T3 provides the ability to save all of your measurements. The Accu-Gold T3 system consists of a built-in digitizer module whose function is to transform the analog signals generated by a host of sensors into calibrated digital signals. The T3 is available in different models that are suited for specific applications, the differences being which sensors can be used.

System Configuration Options and Capabilities						
Model Number	Accu-Gold T3 AGT3-AG	Accu-Gold T3 Pro AGT3-P-AG	Rapid-Gold T3 AGT3-RG	Rapid-Gold T3 Pro AGT3-P-RG	Accu-Dose T3 AGT3-AD	Accu-Dose T3 Pro AGT3-P-AD
Standalone Operation	X	X	X	X	X	X
AG3 USB Connection		X		X		X
AG3 Wireless Connection		X		X		X
Sensor Options						
AGMS-D+ AGMS-M+ AGMS-DM+	X	X	X	X		
Ion Chambers	X	X			X	X
Dose Diode	X	X	X	X	X	X
mAs Sensor	X	X	X	X		
Light Sensor	X	X				

The T3 will auto-switch between two different viewing angles



Touch screen



ON/OFF

USB Flash drive connector (used for measurement export and firmware or profile updates)

Power and Status LED (see legend on unit for meaning of colors). See [chart](#) for additional details.

Charging and USB Mode connector

IC (Ion Chamber),
DD (Dose Diode)
connectors

Caution: All connectors are push-pull – do not twist

Setting up the Hardware

1. Connect the sensor(s) to the T3.

2. Position the sensor to make a measurement.

Note: Position the sensor before starting the T3; moving the sensor or cable while it is measuring may trigger a false measurement.

3. Place the sensor in the path of the X-ray beam.

Note: Make sure the temperature of the ion chamber (if used) has stabilized* before making a measurement.

4. The unit will have Quick-Start on and will choose a profile automatically.

Turn on the T3. The unit will automatically go into measure mode.

5. The firmware begins to initialize the hardware as indicated by the status at the bottom of the screen. If an ion chamber is connected, the bias supply needs to start and stabilize.

6. As soon as the “READY” message is displayed at the bottom of the screen, you can make a measurement.

7. Activate the X-ray machine to capture the exposure data.

8. The T3 automatically saves and displays the data for the measurement when the exposure is complete.

9. At any time you can review outputs of the current measurement or previous measurements. Make additional exposures as necessary.

Note: All measurements are automatic (except for Manual Trigger Mode) until you press the **Pause** button.

10. If you need to reposition the sensor(s), click the **Pause** button to temporarily take the sensor offline and prevent any inadvertent null exposures from being added to your measurements.

11. Click the **Play** button when you are ready to make your next measurement.

Measurements Using Solid State Mammographic Sensors

If using the multisensor for mammography, go to Manual Mode to choose the appropriate Anode-Filter (see [Manual Mode](#)).

Radcal sensor calibrations assume that a 2.2 mm polycarbonate paddle, or the simulated paddle supplied with the multisensor (Model 8154), is placed on top of the sensor.

Making a Measurement with multiple sensors connected

The Accu-Gold T3 allows you to connect up to five sensors (depending on model – see System Configuration Options and Capabilities) simultaneously and collect data from all of the connected sensors.

*For changing environments, allow 10 minutes for every 10 C difference for the sensor/electronics to equilibrate.



Quick Start

Plug in your sensors, start the T3 - you are ready to make measurements ...

The screenshot shows a dark-themed control interface for a measurement system. At the top left is a home icon (house symbol) circled in red, with an arrow pointing to the text "Takes you to the Home screen". To its right is a "Session" menu icon (three dots) also circled in red, with an arrow pointing to the text "Session title". The main display area contains several data fields: "AGMS Ave. kV" with a value of "n.a. kV", "AGMS Dose" with "n.a. Gy", "Duration" with "n.a. s", "AGMS Rate" with "n.a. Gy/s", "AGMS HVL" with "n.a. mm-Al HVL", and "AGMS Filt." with "n.a. mm". A status bar at the bottom shows a yellow play button icon, a yellow pause button icon, and the word "READY" in white, all enclosed in a red circle. Arrows point from the "READY" text to the text "Indicates system is Ready to make a measurement." and from the play/pause icons to the text "Press Pause or Play". On the left side of the slide, there are two legend items: "Play" with a yellow play button icon and "Pause" with a yellow pause button icon. The text "Touch play when the sensors are in place." is next to the play icon, and "Touch pause before moving sensors or cables." is next to the pause icon.

Takes you to the Home screen

Session title

AGMS Ave. kV n.a. kV

AGMS Dose n.a. Gy

Duration n.a. s

AGMS Rate n.a. Gy/s

AGMS HVL n.a. mm-Al HVL

AGMS Filt. n.a. mm

No Wave for Exposure

Play Touch play when the sensors are in place.


Pause Touch pause before moving sensors or cables.

Indicates system is Ready to make a measurement.

Press Pause or Play


Make your first measurement...

Data shown is the real-time data as the exposure is happening




Measurement has been triggered

After the exposure the values are updated by the post-exposure results and the waveform is displayed.



The Main Menu



If you attach the sensor before you start, the software will go straight to measuring* (see previous page). Otherwise, click on **Quick-Start** to start.

*This can be overridden in the Settings menu: "[Auto-Start Measurement](#)"

If the choices made by Quick-Start are not appropriate** for the measurements you are making, choose **Manual Mode** or select a profile from the Profile Library.

If you are continuing a previous session, choose **Sessions**.

Battery charge level

Connection method


**Quick-Start will look to see what sensors are attached and will automatically choose the appropriate profile. Note: when using the DM sensor, it will choose the W-AI diagnostic calibration as the default. If you are making Mammo measurements, you will have to choose the appropriate A-F manually.



Level




Charging




Error

The Manual Mode




Choose the sensor to use for triggering the measurement


Before making an exposure, make sure to choose the Anode/Filter combination that matches the machine being measured.



The Accu-Gold Digitizer Module (AGDM) allows you to simultaneously collect data from multiple sensors.



The Manual Mode (cont)



Many x-ray feature scout exposures may introduce gaps of several seconds or more in the radiation output. The default end of exposure timing in some instances will not be long enough and Accu-Gold may attempt to display the exposure results while the generator is still finishing the exposure. If this situation is encountered, you may select an end of exposure delay of up to 8 seconds. Min allows one to make successive measurements quickly. In between measurements, zeroing is skipped and therefore use Min with large signals only where zeroing in between measurements is not important – use with “High Trigger Level”.

High – Select if Std causes false triggering.

Low - Select if Std is not low enough. Low may allow smaller signals to be captured, but may also result in false triggers.

Std - Std trigger sensitivity is recommended.




Note: If noise or false triggers prevent reliable ion chamber measurements and grounding the system has not improved the experience, connect a Multi-sensor or Dose Diode and locate it somewhere in the radiation beam so that it can serve as a trigger source. (refer to Application Note [AN1007](#)* for more information)

If you have a strong, noise free signal, selecting High will minimize the time the system measures a background zero in between measurements allowing you to make continuous measurements rapidly. A new zero will be recalculated every 5 minutes.


*<https://radcal.com/download-application-notes/>

The Profile Library

When you don't get the desired result using Manual Mode, a suitable profile might be available based on Modality or Manufacturer.




The Profile Library (cont)



Profile selection

Use this if a custom profile has been supplied to you.

Describes the suggested usage conditions for the profile



Returns to previous screen


Profile information

The Measure Screen

Opens mini-menu

This will open the [Sessions](#) management screen.


A new session is started automatically. Use this if you want to start a new one.



Sensors

Timestamp	2024-07-19 16:09
Mode	Auto
Calibration	W/AI Diagnostic
Profile file	agms1_std_10.agp
Sensors	MS 43.0001

Information about the sensors and what measurement configuration is being used.




The main Measure Screen displays various measurement parameters:

- AGMS Dose: 29.37 mGy
- AGMS Rate: 22.51 mGy/s
- AGMS HVL: 4.73 mm-Al HVL
- AGMS Filt.: 3.32 mm

At the bottom, it shows a 'READY' status and a graph area. A mini-menu is open, listing options: Open Sessions, Start New Session, Rename Session, Sensors, and Delete Measurement.

Allows you to name the current session

Returns to Profile selection screen or where you were last




This deletes the current measurement permanently. Are you sure?

Yes Cancel


Deletes the current measurement only

The Measure Screen

While making the measurement, the screen will expand* to make it easier to see the data from a distance. The screen will revert back to the original size after 5 seconds.




Touching a cell will zoom that one cell out to the size of the screen in order to see the values even further across a room. Touch again to go back to regular size. Measurements can be made while the cell is expanded.



As the sensors react to an exposure, the screen expands and a wide yellow band indicator can be seen across the room.

*This can be changed in the Settings menu: "[Automatic Fullscreen on Trigger](#)"

The Measure Screen (cont)




If an ion chamber is used, on the first measurement it will require that you wait 60 seconds while the bias supply stabilizes. Touching "Skip" terminates the recommended stabilizing time.

Touch the waveform anywhere to expand it (see next page)

The Measure Screen (cont)



Touching the small waveform on the measurement screen will fill the screen with the waveform in order to see more detail. Touch the 'X' to return.



Returns to Measure screen

The Measure Screen (cont)

Touch the comment icon to open the Details View.




Returns to Measure screen

Touch the pencil and you can add comments to the measurement using the built-in keyboard.

Checking the box will copy the Comment to the next measurement.

Touch the 'X' to return.




Customizing the Screen

The screen can be customized to display different result values. There are two Standard display profile pages and two Custom pages that can be modified. The Standard pages will update based on the sensors being measured. The Custom pages will always show the values you have chosen.




Standard display profiles

Custom display profiles



Select the underlined title to change to display a different measurement result value:



Gen results are measured by sensors in the digitizer itself.

Customizing the Screen (cont)

The screenshots illustrate the following configurations:

- Gen:** Air Pressure, Trigger Duration
- AGMS:** kVp, Dose / Pulse
- IC:** Peak Average Rate, Rate
- DAP:** Duration, Empty
- DLP:** Average kV, Filtration
- DD:** Peak Average Rate, HVL
- mA:** Biased Average kV, Overall Dose Rate
- Lum:** Dose, PPV
- DAP+:** Dose / mAs, Pulse Count
- Dyn:** Dose / mAs, Pulse Count

Additional configurations shown in the second row:

- DAP:** Peak Average Rate, Temperature
- DLP:** Dose Area Product / mAs
- DD:** Dose Area Product
- mA:** Dose Area Product / Pulse
- Lum:** Dose Area Product Rate
- DAP+:** Dose Area Product Rate
- Dyn:** Overall Dose Area Product

Additional configurations shown in the third row:

- AGMS:** Peak Average Rate, Temperature
- DAP:** Dose Length Product
- DLP:** Dose Length Product / mAs
- DD:** Dose Length Product / mAs
- mA:** Dose Length Product / Puls
- Lum:** Dose Length Product Rate
- DAP+:** Dose Length Product Rate
- Dyn:** Overall Dose Length Produ

Additional configurations shown in the fourth row:

- DD:** Dose Ratio DD / IC, Rate
- DLP:** Dose Ratio DD / AGMS
- mA:** Dose
- Lum:** Dose / mAs
- DAP+:** Dose / Pulse
- Dyn:** Dose / Pulse

Additional configurations shown in the fifth row:

- mA:** Charge
- Lum:** Charge / Pulse
- DAP+:** Current
- Dyn:** Overall Current

Additional configurations shown in the sixth row:


- Lum:** Illuminance
- DAP+:** Luminance
- DAP:** Dose Area Product
- DLP:** Dose Area Product / Pulse
- DD:** Dose Area Product Rate
- mA:** Overall Dose Area Product
- Lum:** Temperature
- DAP+:** Temperature
- Dyn:** Temperature

Additional configurations shown in the seventh row:

- DAP+:** kV
- Dyn:** PPV, kVs

The default kV measurement is Average kV. See [AN1016](#) for more information on the different types.

Sessions




Data on the T3 is segregated into sessions. Every time the T3 is turned on, a new session is automatically created and automatically saved when turned off. Use "Start New" to create additional session groups without turning off the unit.

Adding data to a previous session is possible by touching the '>' symbol.


Sessions can be titled to identify the locale where the data were taken.

The data can be exported to a flash drive to share the data or create additional reports.


* = Current session



Touch the three dots to bring up this menu:



This will delete only the one session.





This will delete all data on the T3.

Note: only values will be exported, wave data will not.


Number of measurements in the session

This will start a new session without turning off the unit.

The Sessions screen (cont)





Insert a USB flash drive into the unit first. All of the T3 data will be exported. The exported sessions are compatible with AG3 (install AG3 first). Note: do not use a USB flash drive that was used for a firmware upgrade.



The flash drive will contain .agx files that correspond to the session files from the T3. Measurement data can be viewed using AG3 and then exported to Excel if desired. (Note: Wave data will not be available)

The Settings Menu - System




Turns on/off the sounds generated during measurements

The unit will dim the display after 30 seconds and power off after 30 minutes of no activity unless turned off here.

The unit will go into Quick-Start when turned on unless turned off here.


When making a measurement, the measure screen will automatically expand to full screen making the measurement values bigger. After approximately 5 seconds, it will go back to normal size. You can also choose the length of time it waits or turn off this feature:



Permanent will leave it expanded until you manually restore it by tapping the screen.

Measurements and sessions include time information. If the time needs to be set, touch Set

Touch up or down arrows to set the time. When done, select the Back arrow to continue.





The Settings Menu – Connections – WiFi Access Point

The T3 Pro can work in sync with AG3 wirelessly using a Wi-Fi connection. This can be done one of two ways –

1. **WiFi Access Point** (the T3 and AG3 create their own network) or
2. WiFi Network Join (the T3 and AG3 communicate on an existing network)

The T3 needs to be setup first before AG3.

Select WiFi Access Point and enter the password: 12345678




In Windows -

You will need to tell your PC how to connect to the T3:

Press the Windows key and start to type 'WiFi settings'.




Then select 'WiFi settings'.



Make sure Wi-Fi is 'On' on your computer then select 'Show available networks'




You will see 'T3_56-xxxx' with the serial number of your unit in the list. Click 'Connect' and enter 12345678 as the password.



Now open AG3 and select WiFi Sync, then Connect.




The Settings Menu – Connections – WiFi Network Join





Scanning for available WiFi networks...


The available networks will be shown. Select the one you want



You will be asked for the network logon information:



When the connection is made to the WiFi network:





Now open AG3 and select WiFi Sync, then Connect.



The Settings Menu – USB mode

The T3 Pro version can work in sync with AG3 also by using a USB cable, thru a USB connection.




Connect your computer USB connection to the T3 USB using a USB cable with a 'micro-USB' connector.



A Male to Micro B Male shielded with ferrites.

In AG3, choose Connection then "USB AGDM+"



See [AG3 manual](#) for more information

The Settings Menu - Units

The screenshot shows the 'Settings' menu with the 'Units' section highlighted. The settings are as follows:

Setting	Current Value
Dose Unit	Gray
Dose Scaling	None
Time Base for Rate	1/sec
DAP Area Unit	m ²
DLP Unit	cm


Callouts show the available options for each setting:

- Dose Unit:** Gray, Roentgen
- Dose Scaling:** Auto, Micro, Milli, None
- Time Base for Rate:** 1/sec, 1/hour, 1/min, 1/sec
- DAP Area Unit:** cm², cm², m²
- DLP Unit:** cm, cm, m

Dose Area Product (DAPCHK or 10X6-60DAP) measurements can be displayed in cm or m units of area

Dose Length Product (CTDI chamber) measurements can be displayed in cm or m units

The Settings Menu - About



Firmware Version – when an update is available compare this number against the version listed on the update page:

<https://radcal.com/download-accu-gold-software/>

Custom Profiles -


Profiles allow one to make highly technical measurements without the hassle of setting up the parameters each time. They tell the computer the calibration file to use, the timing required, the sensors to use and so on. They allow you to set a region of interest (ROI) which gives you details on certain areas of the measurement.

Combo-mode profiles allow you to quickly make the multiple measurements with a single exposure of the x-ray machine when the x-ray machine is changing anode-filters internally. This makes it possible to save precious time and hassle and gets you in and out in a hurry.

So what happens when there is no profile for what you need? Contact Radcal to discuss your needs and we will assess your situation. We will make a profile that is suited for your specific needs. If this is a general need, we will incorporate the profile in our profile library and release it in the next version of the software.


If it is a general profile that is added to the profile library, update the software and find it there. If it is a custom profile, the profile we send you will need to be loaded onto the T3 to be used.

To import the custom profile, load it on a removable USB drive (flash drive) and plug it into the T3. Select Profile Library from the Home menu, then select Custom:



Select Scan. All profiles, regardless of the folders they are in on the flash drive, will be considered.

Select Yes



Differences between T3 and AG3

T3 is a portable/wireless version of AG3 with a few exceptions. As T3 development continues, future releases will provide enhancements to minimize them. The major differences are:

- With AG3, it is possible to reanalyze a session recorded recently. Since the T3 does not yet save raw data, it does not have the ability to reanalyze.
- T3 limits the maximum amount of wave data that can be captured in a single exposure. When this limit is reached, the measurement continues but the wave data is lost. We expect that this limitation can be eliminated in a future release.

LED Color code

The label on the back of the unit summarizes the meaning of the different colors for the LED that is next to the USB connector. This table details the other possible combinations and their meaning.

LED Color	Meaning
GRN steady	Power On
GRN/RED blinking	Low Battery
YEL/GRN blinking	Charging OK
YEL/RED blinking	Charging/Power Low
YEL steady	Battery Charged
BLU steady	Error (Fuel Gauge)
RED steady	Error (Battery)
WHT steady	Saving Data

Specifications

Specifications

[Ion Chambers](#)

[10X6-6](#)

[10X6-6M](#)

[10X6-10](#)

[10X6-60](#)

[10X6-60DAP](#)

[10X6-3CT](#)

[10X6-180](#)

[10X6-1800](#)

[10X6-0.18](#)

[10X6-0.6](#)

[10X6-0.6CT](#)

[10X6-500](#)

Solid State Multisensors

[_Specifications](#)

[_Dimensions](#)

[Solid State Dose Sensor](#)

[Current Sensors](#)

[Light Sensor](#)

[DAP Calibration Sensors](#)

Declaration of Conformity

See <https://radcal.com/downloads-conformity/>

Making Low Level Measurements Using Ion Chambers

When making low dose measurements using an ion chamber (in the range of 10 times the minimum rated range), it is important to eliminate all sources of noise including noise induced by changing temperatures of the surroundings and the electronics. Position the ion chamber. Set the threshold to low and wait 3 minutes. Do not touch the cable or digitizer. For changing environments, allow 10 minutes for every 10 C difference for the sensor/electronics to equilibrate. Grounding the system to eliminate interference may be warranted.

Automatic temperature and pressure compensation for the unsealed ion chambers is provided. Temperature-compensation accuracy is equivalent to 0.5°C (0.2%) between 15 and 35°C. Temperature is measured at the ion chamber connector. Pressure-compensation accuracy is equivalent to 0.5 kPa between 60 and 105 kPa. Pressure is measured in the digitizer module.

Accu-Gold T3 Specifications –

Display Specifications

Resolution: 800 x 480

Touch Type: Capacitive Touchscreen

Type: LCD TFT TN equipped with chemically tempered float glass, pencil hardness 7H, LED backlighting

Orientation: 35° or 60°. Display automatically flips based on unit orientation.

Environmental Specifications

Operating temperature: 15 °C to 35 °C

Pressure: 60 to 105 kPa

Humidity: Up to 80% RH or 20 g/m³

Storage: Temperature 0 °C to +60 °C

USB ports

Flash drive: Standard USB A 2.0

Charger/USB mode(T3 Pro): Standard USB B 2.0 micro

Wireless Communication Specifications (T3 Pro)

Network Standard Support: IEEE 802.11b/g/n

Frequency band: 2.400 - 2.472 Ghz, channels 1-11

Antenna power: <10 mW/MHz

Connectivity: Access Point mode

Wireless Security: WPA2 secure encryption

Networking Protocol: TCP

Regulatory Approvals: EU (ETSI), FCC, IC (Industry Canada), China (CMITT), KC (Korea), Japan (MIC)

Caution

Do not dispose of product in heat, fire or water. Misuse, dropping, or excessive force may cause product damage.
(Recycling manual available on request)

Power Specifications

Battery: 5.5 Ah Li-Poly (single-cell) – not user serviceable

Battery Life: > 8 Hours under normal usage

Charging Time: <5.5 Hours (maximum to fully recharge)

Charger: Radcal part number PRS/PSA10F-050 (5V, 2.0A)

Input: 90 to 264 VAC, 47 to 63 Hz

AC power supply blades (international kit) PRS/PSA10F-Q (D)

Compliance (see <https://radcal.com/downloads-conformity/> for Declaration or Conformity)

The Accu-Gold T3 Basic and Pro models conform to ISO/IEC/UKCA requirements: Electromagnetic Compatibility Regulations, Electrical Equipment (Safety) Regulations, the Restriction of the Use of Certain Hazardous Substances in Electrical and Electronic Equipment Regulations.

Performance: IEC 61674, IEC 61676

Environmental Directives:

1. Radcal meets the requirements of the 2002/06/EC (WEEE) Directive, category 9, and has implemented full compliance. (Manuals are available on request.)
2. Radcal meets the requirements of the 2015/863/EU (RoHS3) Directive.
3. The Accu-Gold/Rapid-Gold/Accu-Dose+ comply with China RoHS marking and EFUP pursuant to clause 6.2 of SJT/11364:2006 for Electronic Information Products.
4. Radcal meets the requirements of the EC1907/2006 (REACH) Directive

T3 Wireless Radio Regulatory Information

Wireless Radio Information –
WiFi Module ESP32-C3-WROOM-02
Espressif Systems
Operating at 2.4GHz

FCC:

Contains FCC ID: 2AC7Z-ESP32C3WROOM
This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.

EU (ETSI):

This device is intended for home and office use in all EU countries and other countries following the EU directive 2014/53/EU.

China PRC (CMIIT)

The equipment contains the RF modules of which Type Approval code is CMIIT ID: 2021DP3225

Industry Canada Statement:

Contains: IC: 21098-ESPC3WROOM
This device complies with RSS-210 of the Industry Canada Rules.

Japan (MIC)

Contains: Telec Construction Certification Number 201-220555
This equipment contains specified radio equipment that has been certified to the Technical Regulation Conformity Certification under the Radio Law.

Korea (KC)

R-C-es5-ESP32C3WROOM02

Warranty for the Accu-Gold Measurement System

Radcal warrants that, in the event that any defects in material or workmanship should develop within one year of the date of shipment, the company assumes full responsibility for servicing equipment of its manufacture without charge upon return of the equipment to Radcal, with shipping costs prepaid by the customer. Costs to return-ship to customer by ground transportation will be paid by Radcal if the repairs are warranty-applicable. This warranty excludes batteries. Radcal shall not be held liable for damages or delays caused by defects beyond making repairs or furnishing replacement parts, nor shall Radcal be liable for any defective material replaced without Radcal's consent during the period of this warranty. Radcal reserves the right to perform warranty services at its own factory.

Non-Warranty Repairs

The calibration of this instrument was correct within specified limits when the instrument left our factory. Radcal cannot be responsible for injury or damage resulting from improper use or calibration errors which develop subsequent to our shipment of the instrument. If Radcal determines that a fault has been caused by misuse, abnormal operating conditions, or repairs by unauthorized personnel during the warranty period, repairs and shipping costs will be billed at normal rates. If the equipment is found to be in proper working condition, Radcal will return-ship the equipment at customer expense.

Software Limitations

- Maximum disk / flash space reserved for raw data recordings
 - AG3: **512MB** (oldest ones will be deleted when reaching limit)
 - T3: **128MB** (space is reserved, but raw data saving is not implemented yet)
- Maximum measurement length, due to configuration measurement profiles:
 - AG3: **300s**
 - T3: **120s**
- Maximum measurement length **with wave data**:
 - AG3: **300s** (Caution: This will probably be changed to a lower value because of RAM issues on less capable systems)
 - T3: **120s** (Wave is only rendered in a lower resolution for preview.) The number of sensors does not impose restrictions.
- Maximum measurement count per session:
 - AG3: **On less capable systems, max 20 exposures per session. (Subject to change in the future) - there is no enforced limit**
 - T3: **Unlimited - but 300 measurements per session are displayed**
- Maximum session count:
 - AG3: **Depending on disk space** (ca. 150KB/Session/Measurement)
 - T3: **last 75 sessions displayable**

- T3:
 - No raw data recording.
 - No reanalyze of measurements.
 - No export of single sessions (all sessions can be exported)
 - No import of sessions



426 West Duarte Road
Monrovia, CA 91016-4591 USA
USA (626) 357-7921
Fax USA (626) 357-8863
email sales@radcal.com
www.radcal.com

Customer Support -
cust_sup@radcal.com

Radcal Part # MNL/T3
4094518 Rev: A
Firmware V3.8.5 & on
Printed: Jul 2025

